Ultrasonic Sensor

multicomp PRO



Applications

Applications include Burglar Alarms, Distance Measurement, Range Finders, Remote Controllers & Robotics, etc.


Features


- High reliability
- · Compact and light weight
- · Open structure and dual use (Transmitter & Receiver)
- High sensitivity and sound pressure
- Less power consumption


Technical Terms

Construction	: Open Structure
Using Method	: Dual Use (Transmitter & Receiver)
Frequency	: 40 ±1kHz
Sound Pressure Level	: min. 110dB (10V/30cm)
Sensitivity	: min65dB/V/µbar
Capacitance	: 2500pF ±25% @ 1kHz
Directivity	: 50°
Operating Temperature Range	: -40°C to +85°C
Storage Temperature Range	: -40°C to +85°C
Detectable Range	: 0.7 to 18m
Maximum Input Voltage	: 60Vp-p
Housing Material	: Aluminium

Diagram








Tolerance : ±0.5 Dimensions : Millimetres


Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

multicomp PRO

Beam Pattern:



Test Circuit:



DescriptionPart NumberUltrasonic Sensor, Transceiver, 16mm Dia,
40kHz, -65dB, Aluminium, Silver, -40°C to 85°CMCUSD16A40S12RO

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet sheet sheet sheet henck for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro sg.element14.com/b/multicomp-pro

